

## Hilltopper20 Parts list:

Qty.	Reference designator	Description	Notes/ markings
2	C6, C15	10 pF C0G cap	"100"
2	C40, C41	22 pF C0G cap	"220"
4	C1,C8,C12,C16	47 pF C0G cap	"470"
1	C3 - <b>20M</b>	47 pF C0G cap	Band Pack "470"
1	C53	12-60 pF trim cap	brown
1	C17	68 pF C0G cap	"680"
1	C52 - <b>20M</b>	68 pF C0G cap	Band Pack "680"
3	C7,C9,C11	100 pF C0G cap	"101"
1	C10	150 pF C0G cap	"151"
1	C2 - <b>20M</b>	150 pF C0G cap	Band Pack "151"
1	C49 - <b>20M</b>	220 pF C0G cap	Band Pack "221"
1	C51 - <b>20M</b>	270 pF C0G cap	Band Pack "271"
2	C21,C24	470 pF C0G cap	"471"
1	C50 - <b>20M</b>	470 pF C0G cap	Band Pack "471"
1	C22	220 pF C0G cap	"221"
1	C26	820 pF C0G cap	"821"
1	C27	.0022 (2200 pF) C0G cap	"222"
10	C4,C5,C13,C14,C31,C37,C38,C39 C47, C54	.01 uF cap	"103"
1	C18	.033 uF cap	"333"
15	C19,C20,C23,C25,C28,C32,C33, C34,C35,C36,C42,C44,C45,C46 C48	0.1 uF cap	"104"
3	C29,C30, C43	100 uF electrolytic cap	

All resistors are  $\pm 5\%$  tolerance  $\frac{1}{4}$  watt.

2	R13, R23	4.7 ohm	Yellow-violet-gold-gold
2	R14, R15	470 ohm	Yellow-violet-brown-gold
1	R22	1.0K ohm	Brown-black-red-gold
2	R1, R16	5K potentiometer, PCB mount	
8	R2, R3, R11, R17-R21	10K ohm	Brown-black-orange-gold
1	R8, R9	22K ohm	Red-red-orange-gold
1	R8	47K ohm	Yellow-brown-orange
1	R4	150K ohm	Brown-green-yellow-gold
1	R5	330K ohm	Orange-orange-yellow
1	R10	510K ohm	Green-brown-yellow-gold
3	R6, R7, R12	1.0M ohm	Brown-black-green-gold
1	CAL	2-pin male header, .100"	
1	CAL	2-pin female jumper	

1	D1	1N5818 diode	Black case
4	D2, D3, D4, D5	1N4148 diode	Glass case, small
2	D6, D7	BAT85 diode	
1	D8	1N4756 diode	Glass case, larger

## Hilltopper20 Parts list Continued:

1	J1	BNC jack, right-angle mount	
1	J2	DC power jack	
2	J3, J4	Key and audio jacks, 3.5mm 3-cond.	
--	J5	6-pin .100" male header	not supplied in kit
--	J6	4-pin .100" male header	not supplied in kit

1	L1 – <b>20M</b>	3.3 $\mu$ H RF choke	Orange-orange-gold-gold
1	L2 – <b>20M</b>	3.3 $\mu$ H RF choke	Orange-orange-gold-gold
2	L3, L4	18 $\mu$ H RF choke	Brown-grey-gold-gold
1	L5	FT37-43 toroid	See group 7 instructions
2	L6, L7 <b>20M</b>	T37-6 toroid	See group 7 instructions

5	Q1, Q3, Q5, Q6, Q7	BS170 MOSFET	
1	Q2	J113 JFET	
1	Q4	NTD2955	Small heat sink tab
2	U1, U2	SA612AD 8-pin SOIC-8 IC	(pre-installed)
1	U3	NJM4556AD	8-pin DIP IC
1	U4	LM78M05	Small heat sink tab
1	U5	ATmega328P	28-pin DIP IC
1	U6	LM78L05	
1	U7	74AC08	14-pin DIP IC

### Miscellaneous:

1	--	Si5351 board	Supplied with 8-pin header strip. See group 3.
1	SW1	pushbutton switch	
2	--	1/16" plastic spacer	Used with pushbutton sw
1	SW2	rotary encoder w/ switch	
5	X1-X5	5.185 MHz HC-49/US crystal	Matched set
1	X6	16 MHz HC-49/US crystal	
1	--	#24 magnet wire <b>20M</b> – Band Pack	18" (45 cm) length
1	--	#21 magnet wire <b>20M</b> – Band Pack	24" (60 cm) length
3	--	Knobs	
4	--	1/4" #6 spacer unthreaded	
4	--	5/8" #6 spacer, threaded	
4	--	#6-32 x 1/4" machine screw, pan head	
4	--	#6-32 x 3/8" machine screw, pan head	
1	--	8-pin DIP socket	
1	--	14-pin DIP socket	
1	--	28-pin DIP socket	